POWERTEC | DATASHEET | UNCONTROLLED WHEN PRINTED PUBLIC | August 8, 2025 19:00

Page



Powertec Wireless Technology ABN: 42 082 948 463 PO Box 1034, Ashmore City Queensland, Australia, 4214 sales@powertec.com.au 1300 769 378

Nextivity Cel-Fi GO G32-1/3/5/7/8/20X Repeater

SKU RPR-CF-00392 MPN G32-1/3/5/7/8/20X

Description

The Cel-Fi GO G32 is a highly effective repeater designed to improve Optus mobile voice, text, and data coverage. This model has been designed to improve both Optus 3G and 4G services in a matter of minutes.

Setting up the repeater to improve indoor mobile coverage is simple. The unit has an input connection and an output connection which are set up as follows:

- Input connection: connected to roof mounted antenna by cable
- Output connection: can either connect directly to an antenna, or can use one or more cables to distribute signal elsewhere.

Read More

The Cel-Fi GO G32 works by decoding and amplifying weak Optus signal detected by the roof mounted antenna. This signal is then boosted up to 100 dB using a linear amplifier and output through the antenna or series of antennas connected to the output port.

Unique to the GO G32, the repeater is IP66 ingress protection rated and built tough for use in outdoor and tough environments.

The Optus Cel-Fi GO G32 can operate on two frequency bands simultaneously, providing either 3G and 4G coverage, or 2C 4G LTE-Advanced for higher data speeds.

Read More





Nextivity

Nextivity, Inc. develops and sells in-building cellular coverage technology products and solutions. The Company helps wireless subscribers and increases radio frequency network capacity for mobile network operators. Nextivity operates in the State of California.

Nextivity is best known for its Cel-Fi range of mobile repeater solutions which provide low cost improved in-building coverage solutions.

RF Specification

Simultaneous Bands 2 Downlink Max. Gain 100 dB Supported Technologies 3G UMTS, 4G LTE Relay Bandwidth 40 MHz Uplink Max. Gain 100 dB Supported Bands

| Frequency Band | Duplex Method | мімо | Max. Channel Width | Downlink Start Frequency | Downlink Stop Frequency | Uplink Start Frequency | Uplink Stop Frequency |
|--------------------------------|------------------|---------------------------|--------------------------|--------------------------------|-------------------------------|------------------------------|-----------------------------|
| <u>B1 (2100</u> <u>MHz)</u> | <u>FDD</u> | <u>1x1</u> SISO | 20 MHz | 2110 MHz | 2170 MHz | 1920 MHz | 1980 MHz |
| <u>B3 (1800</u> MHz) | <u>FDD</u> | <u>1x1</u> SISO | 20 MHz | 1930 MHz | 1990 MHz | 1850 MHz | 1910 MHz |
| <u>B5 (850</u> MHz) | <u>FDD</u> | <u>1x1</u> SISO | 15 MHz | 869 MHz | 894 MHz | 824 MHz | 849 MHz |
| <u>B7 (2600</u> <u>MHz)</u> | <u>FDD</u> | <u>1x1</u> <u>SISO</u> | 20 MHz | 2620 MHz | 2690 MHz | 2500 MHz | 2570 MHz |
| <u>B8 (900</u> MHz <u>)</u> | <u>FDD</u> | <u>1x1</u> <u>SISO</u> | 15 MHz | 925 MHz | 960 MHz | 880 MHz | 915 MHz |
| <u>B20 (800</u> <u>MHz)</u> | TDD | <u>1x1</u> <u>SISO</u> | 20 MHz | 791 MHz | 821 MHz | 832 MHz | 862 MHz |
| | | | | | | | |

RF Connections

RF Connector Function Quantity RF Interface Notes

| Donor Input | 1 | SMA Female |
|----------------|---|------------|
| Service Output | 1 | SMA Female |

Network Interfaces

Wireless Interfaces Bluetooth Interface Protocol <u>Bluetooth 4.2</u> Power Class <u>Class 3</u> Ethernet Interfaces

Physical Specification

Ingress Protection IP66 Mounting Screw / Bolt Dimensions 272.5 × 96.5 × 43.5 mm Compliance/Certifications CE

, R-NZ

,

<u>RCM</u>

,

<u>RoHS</u>

Min. Operating Temperature 0°C Max. Operating Temperature 65°C Weight 0.85 kg Device Power Specifications Max. Consumption 16 W

Power Interface

| Power Connector | Min. Input Voltage | Max. Input Voltage | Voltage Type | Input Current |
|--|-----------------------|-----------------------|-----------------|------------------|
| DC Coaxial, Type A, Female 5.5 x 2.5 mm | 9.6 V | 16.5 V | DC | 2 A |
| Drawing | | | | |



Disclaimer: Although care has been taken to ensure the accuracy, completeness and reliability of the information provided, Powertec assumes no responsibility therefore. The user of the information agrees that the information is subject to change without notice. Powertec assumes no responsibility for the consequences of use of such information, nor for any infringement of third party intellectual property rights which may result from its use. IN NO EVENT SHALL POWERTEC BE LIABLE FOR ANY DIRECT, INDIRECT, SPECIAL, OR INCIDENTAL DAMAGE RESULTING FROM, ARISING OUT OF OR IN CONNECTION WITH THE USE OF THE INFORMATION.

