

# Nextivity CEL-FI Quatra Network Unit, 1/3/7/8

MPN: Q34-1/3/7/8NU\_EXA

## Description

The Cel-Fi Quatra is an enterprise 4G repeater system designed to provide in-building coverage to large facilities and small-medium sized multi-storey buildings.

Quatra is a hybrid repeater design which follows a hub-and-spoke design. The system breaks apart the functionality of an inline amplifier by separating downlink and uplink boost functions between the hub, called the Network Unit (NU), and spokes, called Coverage Units (CU). Specification listed on this page are for the Network Unit only.

The system requires one Network Unit and between one and four Coverage Units which are interconnected by ordinary Ethernet cables. A typical system design would use one CU per floor on a multi-storey building, or one CU per warehouse in an industrial facility. Each CU is powered via PoE from the NU.

Ethernet cables are used to transmit a digital signal between NU and CU, allowing lossless connectivity up to 100 metres and up to 200 metres with a ...

Read More

Quatra must be carefully designed and configured in order to correctly function. As a hybrid DAS unit, mobile network operators require Powertec to conduct extensive RF design, which must be submitted to the operator in order to obtain approval for use.

Q34 (Q1000) has been made End-of-Life by the manufacturer.



### Nextivity

Nextivity, Inc. develops and sells in-building cellular coverage technology products and solutions. The Company helps wireless subscribers and increases radio frequency network capacity for mobile network operators. Nextivity operates in the State of California.

Nextivity is best known for its Cel-Fi range of mobile repeater solutions which provide low cost improved in-building coverage solutions.

Simultaneous Bands:	4	Relay Bandwidth:	75 MHz
---------------------	---	------------------	--------

Downlink Max. Gain:	100 dB	Uplink Max. Gain:	100 dB
---------------------	--------	-------------------	--------

Supported Technologies:	4G LTE
-------------------------	--------

#### Supported Bands

Frequency Band	Duplex Method	MIMO	Uplink Output Power	Max. Channel Width	Uplink Start Frequency	Uplink Stop Frequency
B1 (2100 MHz)	FDD	1x1 SISO	22 dBm	20 MHz	1920 MHz	1980 MHz
B3 (1800 MHz)	FDD	2x2 MIMO	22 dBm	20 MHz	1710 MHz	1785 MHz
B7 (2600 MHz)	FDD	2x2 MIMO	22 dBm	20 MHz	2500 MHz	2570 MHz
B8 (900 MHz)	FDD	1x1 SISO	20 dBm	15 MHz	880 MHz	915 MHz

#### RF Connections

RF Connector Function	Quantity	RF Interface	Notes
Donor Input	2	QMA Female	

#### Network Interfaces

##### Ethernet Interfaces

Interface	Quantity	Function	Signalling	PoE Output
RJ45 Copper	1	LAN Management Port	100BASE-T	
RJ45 Copper	1	LAN Management Output Port	100BASE-T	
RJ45 Copper	4	Link to Coverage Unit (Proprietary Signalling)		802.3at PoE+

## Physical Specification

Ingress Protection:	IP20	Min. Operating Temperature:	0 °C
---------------------	------	-----------------------------	------

Mounting:	Wall / Vertical Surface	Max. Operating Temperature:	40 °C
-----------	-------------------------	-----------------------------	-------

Dimensions:	250 × 188 × 55 mm	Weight:	1.2 kg
-------------	-------------------	---------	--------

Compliance/Certifications:	CE
----------------------------	----

R-NZ

RCM

#### Device Power Specifications

Max. Consumption:	120 W
-------------------	-------

Power Options:	DC Power Input
----------------	----------------

Power Interface

<b>Power Connector</b>	<b>Nominal Voltage</b>	<b>Min. Input Voltage</b>	<b>Max. Input Voltage</b>	<b>Voltage Type</b>	<b>Input Current</b>
DC Coaxial, Type A, Female 5.5 x 2.5 mm	54 V	51.3 V	56.7 V	DC	2.22 A

Disclaimer: Although care has been taken to ensure the accuracy, completeness and reliability of the information provided, Powertec assumes no responsibility therefore. The user of the information agrees that the information is subject to change without notice. Powertec assumes no responsibility for the consequences of use of such information, nor for any infringement of third party intellectual property rights which may result from its use. IN NO EVENT SHALL POWERTEC BE LIABLE FOR ANY DIRECT, INDIRECT, SPECIAL, OR INCIDENTAL DAMAGE RESULTING FROM, ARISING OUT OF OR IN CONNECTION WITH THE USE OF THE INFORMATION.

