

# 2J Phoenix 4G-5G Ultraband MIMO + Dual-Band WiFi-6E + GNSS 4-Port Combo Stud Antenna, 617 to 7125 MHz

SKU: ANT-2J-00033

MPN: 2J6986BGFC 8M

## Description

The 2J Phoenix 4G-5G Ultraband MIMO + Dual-Band WiFi-6E + GNSS 4-Port Combo Stud Antenna (SKU: ANT-2J-00033) is a versatile solution designed for robust connectivity across multiple applications. Operating within a wide frequency range of 617 to 7125 MHz, this antenna is ideal for automotive, marine, telematics, automation, and M2M markets.

Constructed from durable polycarbonate and ASA plastic, the antenna is IP67 rated for superior protection against water and dust, making it suitable for harsh environments. With a temperature tolerance from -40 °C to 85 °C, it ensures reliable performance in extreme conditions. The antenna features four input ports providing 4 RF connections, including 2x2 MIMO 5G for enhanced data throughput and dual-band WiFi-6E for high-speed, reliable internet connectivity.

Additionally, the integrated GNSS element supports GPS and GLONASS with an active LNA, ensuring precise location tracking. This component is...

[Read More](#)



2J

2J is a worldwide supplier of antenna solutions for Automotive, Marine, Telematic, Automation and M2M markets. 2J utilise a plethora of modern engineering tools, from network analysers and anechoic chambers, to simulation software and 3D printers. These tools help reduce design phases, and enable us to react to customers' needs promptly and efficiently.

Over the past decade, 2J has established ...

# RF Specification

## Cable 1: 5GNR

Start Frequency:	617 MHz	Polarisation:	Linear
Stop Frequency:	5925 MHz	Input Impedance:	50
Max. Input Power:	25 W		

### RF Connectors

Ports	RF Interface	Body Shape	Cable Series	Length
1	SMA Male	Straight	A-302	3000 mm

### Frequency Test Data

Start Freq.	Stop Freq.	Peak Gain	Return Loss	VSWR	Azimuth	Avg. Gain	Efficiency
617 MHz	960 MHz	3.1 dBi	> 15.5 dB	< 1.5:1	360°	-4.6 dBi	35%
1427 MHz	2690 MHz	2.7 dBi	> 12.1 dB	< 1.8:1	360°	-5.4 dBi	27%

## Cable 2: 5GNR

Start Frequency:	617 MHz	Polarisation:	Linear
Stop Frequency:	5925 MHz	Input Impedance:	50
Max. Input Power:	25 W		

### RF Connectors

Ports	RF Interface	Body Shape	Cable Series	Length
1	SMA Male	Straight	A-302	3000 mm

## Frequency Test Data

Start Freq.	Stop Freq.	Peak Gain	Return Loss	VSWR	Azimuth	Avg. Gain	Efficiency
617 MHz	960 MHz	3.2 dBi	> 16.8 dB	< 1.4:1	360°	-4.8 dBi	34%
1427 MHz	2690 MHz	2.9 dBi	> 12.8 dB	< 1.7:1	360°	-5.7 dBi	27%

## Cable 3: WiFi

Start Frequency:	2410 MHz	Polarisation:	Linear
Stop Frequency:	7125 MHz	Input Impedance:	50
Max. Input Power:	25 W		

## RF Connectors

Ports	RF Interface	Body Shape	Cable Series	Length
1	SMA Male	Straight	A-302	3000 mm

## Frequency Test Data

Start Freq.	Stop Freq.	Peak Gain	Return Loss	VSWR	Azimuth	Avg. Gain	Efficiency
2410 MHz	2490 MHz	0.2 dBi	> 11.4 dB	< 2:1	360°	-6.1 dBi	25%
4920 MHz	5925 MHz	1.7 dBi	> 18 dB	< 1.3:1	360°	-5.6 dBi	27%

## Cable 4: GPS/GLONASS

Start Frequency:	1575.42 MHz	Input Impedance:	50
Stop Frequency:	1606 MHz	Polarisation:	Right Hand Circular (RHCP)

## Low Noise Amplifier (LNA)

LNA Gain:	28 dBic	Min. Operating Voltage:	1.5 V
Noise Figure:	≤ 1.8 dB	Max. Operating Voltage:	3.6 V
Power Consumption:	< 24.3 mW		

# RF Connectors

Ports	RF Interface	Body Shape	Cable Series	Length
1	SMA Male	Straight	L-100	3000 mm

# Physical Specification

Subtype:	Fin / Stud / Combo	Dimensions:	80 x 74 x 25.6
Input Ports:	4	Ingress Protection:	IP67
MIMO:	2x2 MIMO	Materials:	ASA Plastic, Polycarbonate (PC)
Min. Operating Temperature:	-40 °C	Mounting:	Stud / Bulkhead / Panel
Max. Operating Temperature:	85 °C	Compliance/Certifications:	RoHS

Disclaimer: Although care has been taken to ensure the accuracy, completeness and reliability of the information provided, Powertec assumes no responsibility therefore. The user of the information agrees that the information is subject to change without notice. Powertec assumes no responsibility for the consequences of use of such information, nor for any infringement of third party intellectual property rights which may result from its use. IN NO EVENT SHALL POWERTEC BE LIABLE FOR ANY DIRECT, INDIRECT, SPECIAL, OR INCIDENTAL DAMAGE RESULTING FROM, ARISING OUT OF OR IN CONNECTION WITH THE USE OF THE INFORMATION.

