

GME AT4714BA 4G-5G Spring-Mount Bull Bar Antenna, 690 to 3800 MHz, 580 mm

SKU: ANT-GM-00035
 MPN: AT4714BA

Description

The GME AT4714BA Spring-Mount Bull Bar Antenna is expertly designed for robust and reliable 4G to 5G communication across a broad frequency range of 690 to 3800 MHz. With a compact height of 580 mm, this fibreglass whip antenna is ideal for vehicular applications, offering seamless integration with bull bars. Its sturdy construction ensures durability in various environmental conditions, making it suitable for both urban and remote settings.

The antenna provides a single RP-SMA Female RF connection via a 4500 mm RG-58 cable, facilitating straightforward installation. It operates with a 50 Ω impedance and can handle up to 10 W input power, ensuring consistent performance across its operational frequencies. Its vertical polarisation and 360° azimuth beamwidth ensure comprehensive coverage, while peak gain values up to 5.0 dBi enhance signal reception and transmission efficiency.

GME, a trusted Australian brand with over 60 years of...

[Read More](#)



RF Specification

Start Frequency:	690 MHz	Polarisation:	Vertical (V)
Stop Frequency:	3800 MHz	Input Impedance:	50
Max. Input Power:	10 W	Located in Sydney's west, GME operates from its ...	

RF Connectors

Ports	RF Interface	Body Shape	Cable Series	Length
1	RP-SMA Female	Straight	RG-58	4500 mm

Frequency Test Data

Start Freq.	Stop Freq.	Peak Gain	VSWR	Azimuth
690 MHz	960 MHz	2.5 dBi	< 2.5:1	360°
1710 MHz	2700 MHz	5 dBi	< 2.5:1	360°
3400 MHz	3800 MHz	5 dBi	< 2.5:1	360°

Physical Specification

Subtype:	Whip	Dimensions:	580 x 95 (H x Dia)
Input Ports:	1	Materials:	Fibreglass (GRP)
MIMO:	1x1 SISO	Weight:	1.5 kg

Disclaimer: Although care has been taken to ensure the accuracy, completeness and reliability of the information provided, Powertec assumes no responsibility therefore. The user of the information agrees that the information is subject to change without notice. Powertec assumes no responsibility for the consequences of use of such information, nor for any infringement of third party intellectual property rights which may result from its use. IN NO EVENT SHALL POWERTEC BE LIABLE FOR ANY DIRECT, INDIRECT, SPECIAL, OR INCIDENTAL DAMAGE RESULTING FROM, ARISING OUT OF OR IN CONNECTION WITH THE USE OF THE INFORMATION.

